# Data Sheet

We make sure



# AMILO Notebook Pi 3625 The perfect all-round notebook

Issue November 2008

Version 2

Pages 6

The AMILO Notebook P series combines versatile performance, great technology and a fascinating design.

#### Processor technology<sup>1</sup>

■ Latest Intel® Centrino® 2 processor technology (optional) and Intel® Core™ 2 Duo processor for high-definition digital entertainment experience, blistering performance, longer-lasting battery life and the new wireless standard for connectivity

#### **Operating System**

■ Windows Vista® Home Premium

#### **Entertainment and Multimedia**

- The integrated AMILOcam with low-light technology for great video-quality even in low-light conditions and the built-in array microphone are perfect for Internet telephony (VoIP) and video chats
- 17-inch LCD WXGA+ display with BrilliantView technology for vivid colors, amazing sharpness and impressive contrast
- Enjoy your favorite Hollywood blockbuster on an external display via DVI-I (with HDCP support)

#### More convenience thanks to

- The spill-proof keyboard that protects your notebook against accidentially spilt liquids
- The silent mode function that causes a noticeable reduction in fan noise
- The built-in DVD drive to store and secure data comfortably on the move

#### **Options**

 Great storage capacity with up to two hard disk drives for all your videos, pictures and music files Model: Reveal white





Model: Eclipse black







Operating system and Recovery Operating system	Genuine Windows Vista® Home Premium (32-bit version)
Fujitsu Siemens Computers Recovery Program	Backup and restore the original status of the hard disk and create system restore disks
	or individual recovery media on CD or DVD are included
Product design Color	Reveal white or eclipse black
Architecture System architecture Chipset	Intel® Centrino® 2 processor technology or Intel® Core™2 Duo processor technology Intel® GM45 + ICH9M
Chipset	IIIEW GW43 + ICHBW
Processors¹ Intel® Core™2 Duo processor	P7350 (2.0 GHz, 1066MHz FSB, 3 MB L2 cache) P8400 (2.26 GHz, 1066MHz FSB, 3 MB L2 cache) P8600 (2.4 GHz, 1066MHz FSB, 3 MB L2 cache) T5800 (2.0 GHz, 800 MHz FSB, 2 MB L2 cache) T6400 (2.0 GHz, 800 MHz FSB, 2 MB L2 cache)
Intel® Pentium® Dual-Core	T3200 (2.0 GHz, 667 MHz, 1 MB L2 cache)
Memory Memory speed Memory type Memory modules Max. memory size <sup>1, 2</sup>	2 SO-DIMM memory slots (no memory on board) 800 MHz DDR2 RAM 1024 or 2048 MB 4096 MB
Flash Memory <sup>1</sup> (optional) Flash memory type Flash memory size Flash memory hardware	Intel® Turbo Memory 2 GB or 4 GB Mini card
Drives Hard disk drive HDD type HDD size HDD speed HDD cache HDD capacity <sup>1</sup>	SATA 2.5-inch 5400 rpm 8 MB 160, 250 or 320 GB with single HDD; 500 (2x 250) or 640 (2x 320) GB with dual HDD
Optical disc drive (built-in) ODD type ODD technology ODD read speed ODD write speed	SATA SuperMulti-format DVD burner with double layer (DL) support CD-ROM 24x, DVD-ROM 8x CD-R 24x, CD-RW 16x, DVD+R 8x, DVD-R 8x, DVD+RW 8x, DVD-RW 6x, DVD+R DL (8.5 GB) 6x, DVD-R DL (8.5 GB) 6x, DVD-RAM 5x
Display Display type Aspect ratio Display size Display resolution (intern) Display resolution (extern) Resolution type Reaction time Brightness (typ.) Contrast (typ.) Compliance with standards	BrilliantView LCD 16:10 17-inch 1440 x 900 pixels 1920 x 1200 pixels WXGA+ 16 ms 190 NIT 400:1 ISO 13406-2 class II

**Graphics** 

Dedicated graphics (full name) Dedicated video memory Onboard graphics chip Shared video memory 3D Benchmark 2006

Mobile Intel® Graphics Media Accelerator 4500MHD

Up to 1292 MB shared memory<sup>3</sup>

Up to 800 points (depending on configuration)

DirectX® 10 support

Supporting full HD video experience

Interfaces

Graphic features

Video 1x DVI-I (incl. HDCP support)

Audio 1x line in, 1x microphone in, 1x line out / headphone out combined with

S/PDIF out

Network 1x LAN (RJ-45)

Data 1x eSATA combined with USB, 3x USB 2.0

1x ExpressCard slot (54 / 34 mm)

1x 15-in-1 card reader

SD, miniSD, MicroSD, SDHC

MS, MS-Duo

MMC, RS-MMC, MMC-Micro

MSPRO, MS-PRO Duo, MS-Pro HG, MS-Pro HG Duo, M2

xD picture card

Power supply 1x DC-in

Communication

LAN (Local Area Network) Gigabit Ethernet LAN (10 / 100 / 1000 Mbps)

Built-in WLAN (Wireless Local Area Network)

WLAN brand name Intel® WiFi Link 5100 AGN WLAN type draft-n 802.11a/g/n WLAN max. data rate Up to 300 Mbps WLAN encryption WEP, WPA and WPA2

For use in BE, CH, DK, DE, EE, FI, FR, EL, IE, IS, IT, LI, LV, LT, LU, MT, NL, NO,

PL, AT, PT, SE, SK, ES, CZ, HU, UK, CY

Option<sup>1</sup>:

WLAN brand name

802.11b/g WLAN type WLAN max. data rate Up to 54 Mbps WLAN encryption WEP, WPA and WPA2

For use in BE, CH, DK, DE, EE, FI, FR, EL, IE, IS, IT, LI, LV, LT, LU, MT, NL, NO,

PL, AT, PT, SE, SK, ES, CZ, HU, UK, CY

Multimedia

Support of high-definition audio for S/PDIF output with up to 7.1 channels Audio Audio chip

Realtek ALC662

Speakers 2x built-in speakers (1.5 W each) Microphone Built-in array microphone

Subwoofer

Input device Sound volume via function key

**AMILOcam** 

VGA webcam Image sensor Frames per second 30<sup>5</sup>

Features

Auto focus

Automatic brightness adjustment with status LED (blue: on, red:

streaming / application on)

Low-light technology for great video-quality even in dark

surrounding

Input devices / Control buttons Power button	Located left of the keyboard, back-lighted
Keyboard	Spill-proof keyboard with 85 keys, 21 key number block
Touchpad	Hidden touchpad, with left and right mouse button, touchpad disable function via function key combination (Fn+F6)
Multimedia keys	<ul> <li>Located on top of the keyboard to launch the following applications:</li> <li>Silent mode (reduce noise level / fan speed, by reducing the CPU performance, office applications, Internet and DVD playback are not affected)</li> <li>DVD playback</li> <li>Internet browser</li> </ul>
Hot keys	The following hot keys or key combinations are available  Fn+F1 WLAN on / off  Fn+F3 Mute on / off  Fn+F4 Volume down  Fn+F5 Volume up  Fn+F6 Touchpad on / off  Fn+F7 AMILOcam on / off  Fn+F8 Brightness down  Fn+F9 Brightness up  Fn+F10 Display switch  Fn+F11 Silent mode  Fn+F12 Suspend  Number block
	4 individually configurable quick-start application buttons (A1, A2, A3, A4)
Status indicators	The notebook has 3 status icons:  ■ Power status (& suspend)  Blue (always on): on; Blue blinking: stand by; None: off  ■ WLAN  Blue: on; None: off  ■ Battery charge  Blue (always on): full; Blue blinking: charging;  Red blinking: < 10 % capacity
Security	
Supervisor and user password	Yes
Kensington lock Lid switch (hidden)	Yes Yes
ACPI functions	ACPI 3.0 compliant for Vista requirement  Power on stand by (S1 LCD off)  Stand by / energy saving mode (S3 save to RAM)  Hibernate mode (S4 save to disk)  Off mode (S5 soft off)

Power System	
Battery <sup>6</sup> Battery type <sup>1</sup>	Lithium-lon battery
24.10.19 1940	6 cells, 11.1 V / 2200 mAh (cell) / 4400 mAh (pack) or
Battery runtime (idle mode) <sup>7</sup>	8 cells, 14.8 V / 2400 mAh (cell) / 4800 mAh (pack) Up to 6.4 hours <sup>5</sup> (with 8-cell battery)
Battery runtime (idle mode)	Up to 4.0 hours <sup>5</sup> (with 6-cell battery)
Battery runtime (DVD playback) <sup>8</sup>	Up to 4.0 hours <sup>5</sup> (with 6-cell battery) Up to 4.2 hours <sup>5</sup> (with 8-cell battery)
Battery charging time (idle mode) <sup>9</sup>	Up to 3.0 hours <sup>5</sup> (with 6-cell battery)
Battery charging time (ldle mode)	Up to 2.0 hours <sup>5</sup> (with 8-cell battery) Up to 1.75 hours <sup>5</sup> (with 6-cell battery)
Battery charging time (maximum active mode) <sup>10</sup>	Up to 2.8 hours <sup>5</sup> (with 8-cell battery)
Dattery, abouting time (normal year)	Up to 2.4 hours <sup>5</sup> (with 6-cell battery) Up to 2.2 hours <sup>5</sup> (with 8-cell battery)
Battery charging time (normal use) <sup>11</sup>	Up to 1.8 hours <sup>5</sup> (with 6-cell battery)
Battery charging time (off mode)	Up to 2.0 hours <sup>5</sup> (with 8-cell battery)
	Up to 1.75 hours <sup>5</sup> (with 6-cell battery)
AC Adapter	Dynamic charge supported, ACPI 3.0 supported
Wide Range AC adapter	100 - 240 V AC, 50 - 60 Hz
Output	65 W with 20 V DC, 3.25 A
Energy consumption	
S0 (idle mode)	12.55 W
S0 (max. active mode) <sup>12</sup>	31.20 W
S3 (stand by / energy saving mode)	1.65 W
S4 (hibernate) S5 (off mode)	0.65 W 0.64 W
SS (on mode)	0.04 VV
Noise emission	
Idle mode <sup>13</sup>	27.8 dBA (silent mode off)
Maximum active mode <sup>14</sup>	31.2 dBA (ODD load, silent mode off)
Operating conditions	
Operational	5 °C to 35 °C (ambient temperature)
	10 % to 90 % relative humidity, non-condensing
Dimensions and weight	
WxDxH	400 x 302.5 x 29.0 (front) / 47.0 (back) mm
Weight	3.6 kg <sup>15</sup>
Certifications	GOST (WLAN)
	CE Marking
	R&TTE (WLAN)
Warranty	Country specific terms
	· ·
Application Software Home office	Microsoft® Works
HOME OMCE	Microsoft® Office Home and Student Trial
	Adobe Reader
	Windows Mail (within Vista operating system)
	Windows Calendar (within Vista operating system)
Multimedia	Nero Essentials S (CD / DVD write software)
	Vista DVD Playback Pack (DVD playback software)
	Windows Media Player (within Vista operating system)
	Windows Media Center (within Windows Vista® Home Premium
	operating system)
Internet	Microsoft® Internet Explorer
	Country specific Internet provider
Security	Norman security software solution
Occurry	Norman security software solution

**Accessories** Included AC adapter 65 W First Battery 6 or 8 cells Optional Find out more: www.fujitsu-siemens.com Manuals Manual (on hard disk), quick start guide, safety guide, warranty guide, recovery guide Updates downloadable at http://www.fujitsu-siemens.com **Drivers** 

The configuration described in this document is generic only and non-binding. For the exact configuration of your AMILO, please contact your licensed dealer.

Depending on exact configuration. Please check at your local retailer

<sup>&</sup>lt;sup>2</sup> DISCLAIMER: Up to 1 GB may not be available with 32-bit operating systems due to system resource requirements if system is preinstalled with 4096 MB RAM
<sup>3</sup> Shared video memory size may vary depending on configuration. Used video memory size depends on Microsoft® Windows Vista®

memory management

<sup>- 1024</sup> MB system memory enables up to 268 MB static and shared memory

<sup>- 2048</sup> MB system memory enables up to 779 MB static and shared memory

<sup>- 3072</sup> MB system memory enables up to 1292 MB static and shared memory

<sup>- 4096</sup> MB system memory enables up to 1292 MB static and shared memory

<sup>&</sup>lt;sup>4</sup> An adapter is needed for the following card formats: RS-MMC, MMC-Micro, miniSD, MicroSD, SDHC, MS-Duo, MS-PRO Duo, MS-Pro HG, MS-Pro HG Duo, M2

AMILOcam frame rate can vary significantly depending on the used software application

<sup>&</sup>lt;sup>6</sup> DISCLAIMER: Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Recharge time varies depending on usage. The recharge capacity may decrease after some moths so that the battery lifetime as well as operating time can not be assured for the whole lifetime of the notebook

Tested with Battery Mark 4.0.1 ("power saver mode")

<sup>&</sup>lt;sup>8</sup> DVD playback tested with Windows Media Player

<sup>&</sup>lt;sup>9</sup> Tested with BatteryMon

<sup>&</sup>lt;sup>10</sup> Tested with 3DMark 2003

<sup>&</sup>lt;sup>11</sup> Tested with Vista DVD playback

<sup>12</sup> Tested with 3DMark 2006

<sup>&</sup>lt;sup>13</sup> Tested according to ISO 7779 and ISO 9296

<sup>&</sup>lt;sup>14</sup> Tested according to ISO 7779 and ISO 9296

<sup>&</sup>lt;sup>15</sup> Weight may vary depending on actual configuration